

### MAIN FEATURES

- Emergency driver for LED light fixtures that switches to emergency mode in the event of a power failure
- Allows fixture to operate for up to 90 minutes
- Easy installation directly connects to fixture's AC input
- Constant wattage maintains light for the full emergency runtime without degradation
- Approximately 24 hour recharge time

### CONSTRUCTION + FINISH

- Mounting Center: 8.62"/315mm
- L x W x H = 12.91" x 1.97" x 0.94"/328mm x 50mm x 24mm
- Lithium Battery

### ELECTRICAL + SAFETY

- 120-347V, 50/60Hz
- Input Current: ≤100mA
- Designed for use with Solais fixtures
- Operating temperature: 0°C-50°C

### RATINGS + CERTIFICATIONS

- UL Certified for dry locations
- RoHS-compliant
- Meets or exceeds all NEC, IBC, and Life Safety Code Emergency Lighting Requirements
- Meets CA Title 20 battery charger efficiency standards

### WARRANTY

- 1-year warranty



Product Code	EMI-8W	EMI-25W
Output Power	8W	25W
Input Power	6W max.	12W max.
Luminaire Power	60W max. (0-10V dimming) ≤8W (non-dimming)	150W max. (0-10V dimming) ≤25W (non-dimming)



### Ordering Information Example: EMI/8W

